



CSW SERIES INVERTER Compact Sine Wave on the Go







Pure Sine Wave

Battery Voltage Options

Continuous Output Options

Model Numbers

- CSW412
- CSW1012
- CSW2012
- CSW2012-X

Available For

- Emergency Medical Services
- Marine Systems
- Military Vehicles
- RV Systems
- Trucks
- Utility Vehicles

Available Accessories

- Remote Switch (CSW-RS)
- Transfer Switch (CSW-TS15)

The Magnum-Dimensions CSW Series inverter from Sensata Technologies is a pure sine wave inverter designed to be powerful, yet simple to operate. The CSW will provide you with reliable AC power for troublefree use.

FEATURES

Compact and Lightweight

The CSW provides pure sine wave power from a small footprint designed to fit in tight vehicle and marine spaces. And it is lightweight, so won't weigh you down.

At-a-Glance Status

The inverter's status can be determined at a glance with the easy to read LED light.

Digital Display

The alphanumeric display shows the inverter's battery voltage, total AC output power, along with additional operation codes.

USB Port

Power and charge your USB-enabled device with the available USB port.

GFCI AC Outlet

Plug in two pieces of equipment directly to the CSW and know that the GFCI outlet will quickly stop the flow of electricity should a ground fault occur. The outlet also comes with an LED indicator and test/reset capability.

Automatic Transfer Switch Option

The CSW2012-X automatically switches between shore power and inverter/battery power.



OPTIONS Remote Switch

Use the optional CSW-RS remote switch for even easier on/off access away from the inverter. The CSW-RS comes with a 20' cable.



Transfer Switch

Use the optional 15 amp CSW-TS15 transfer switch to automatically switch AC load connections between utility/generator power and the AC output of the CSW1012 inverter.

CSW SERIES SPECIFICATIONS









| | 0014/440 | 00\4\4040 | 0014/0010 | 0014/0010 1/ |
|--|--|--|--|---|
| | CSW412 | CSW1012 | CSW2012 | CSW2012-X |
| INVERTER SPECIFICATIONS - OUTPUT | | | | |
| Continuous power at nominal DC voltage | 400 watts | 1000 watts | 2000 watts | 2000 watts |
| Peak surge power | 800 watts | 2000 watts | 4000 watts | 4000 watts |
| 10 sec surge power | 400 - 550 watts | 1000 - 1500 watts | 2000-3000 watts | 2000-3000 watts |
| 1 sec surge power | 550-800 watts | 1500 - 2000 watts | 3000-4000 watts | 3000-4000 watts |
| 200 msec surge power | > 800 watts | > 2000 watts | > 4000 watts | > 4000 watts |
| AC output voltage at 12.5 VDC | 120 VAC ± 5% | 120 VAC ± 5% | 120 VAC ± 5% | 120 VAC ± 5% |
| AC ouput current | 3.3 AAC | 8.3 AAC | 16.6 AAC | 16.6 AAC |
| AC output voltage range | 104 - 127 VAC | 104 - 127 VAC | 104 - 127 VAC | 104 - 127 VAC |
| AC output frequency | 60 Hz ± 0.5 Hz | 60 Hz ± 0.5 Hz | 60 Hz ± 0.5 Hz | 60 Hz ± 0.5 Hz |
| AC output waveform | Pure sine wave | Pure sine wave | Pure sine wave | Pure sine wave |
| Total harmonic distortion (THD) | < 3% | < 3% | < 3% | < 3% |
| Transfer Time | NA | NA | NA | < 30 ms |
| USB | 5 V, 750 mA | 5 V, 750 mA | 5V, 2.1 A | 5V, 2.1 A |
| INVERTER SPECIFICATIONS - INPUT | | | | |
| Nominal DC input voltage | 12.5 VDC | 12.5 VDC | 12.5 VDC | 12.5 VDC |
| DC input voltage range | 10.5 - 15.5 VDC | 10.5 - 15.5 VDC | 10.5 - 15.5 VDC | 10.5 - 15.5 VDC |
| Input current | 38 DCA | 94 DCA | 193 DCA | 193 DCA |
| No load draw | < 0.8 ADC | < 1.2 ADC | < 1.2 ADC | < 1.5 ADC |
| Optimum efficiency | > 90% | > 90% | > 90% | > 90% |
| High voltage shutdown | 15.5 VDC | 15.5 VDC | 15.5 VDC | 15.5 VDC |
| Low voltage alarm | 11.2 VDC, audible | 11.2 VDC, audible | 11.2 VDC, audible | 11.2 VDC, audible |
| | | 10.5 VDC, | | |
| Low voltage shutdown | 10.5 VDC | Recover at 11.8 VDC | 10.5 VDC | 10.5 VDC |
| GENERAL FEATURES AND CAPABILITI | ES | | | |
| Transfer relay capability | NA | NA | NA | 30 AAC |
| Display status indictator | LED: Power, Fault | Green, amber, red | LED: Status | LED: Status, Display |
| Digital display | None | Input voltage/current, | Input voltage, output power, | |
| AC receptacles | NEMA 5-15 | output power NEMA 5-15 (GFCI) | warning, and error code NEMA 5-20 (GFCI) | warning, and error code NEMA 5-20 (GFCI) |
| | | o CSA C22.2 No. 107.1, meets FC | , , | NEIVIA 3-20 (GFGI) |
| Listings | | | | 0.00.000 |
| Warranty | One year | One year | One year | One year |
| ENVIRONMENTAL SPECIFICATIONS | | -1 | | |
| Operating temperature | -0° C to +40° C (32° F to 104° F) | | | |
| Nonoperating temperature | -20° C to +60° C (-4° F to 140° F) | | | |
| Operating humidity | 0 to 90% RH non condensing | | | |
| Max operating altitude | 9843' (3000 m) above sea level | | | |
| PHYSICAL SPECIFICATIONS | | | | |
| Dimensions (I x w x h) | 6.9" x 7.9" x 2.3" (17.5 cm x 20.1 cm x 5.8 cm) | 12.63" x 7.0" x 3.5" (32.1 cm x 17.8 cm x 8.9 cm) | 16.3" x 9.1" x 4.3" (41.4 cm x 23.1 cm x 10.9 cm) | • |
| Shipping dimensions (I x w x h) | 7.9" x 6.9" x 3.5" | 15.5" x 8.75" x 5.63" (39.2 cm x 22.3 cm x 14.3 cm) | 19" x 11.3" x 6.7" (48.3 cm x 28.7 cm x 17 cm) | 19" x 11.3" x 6.7" (48.3 cm x 28.7 cm x 17 cm) |
| Mounting | | ulkhead (DC terminals MUST b | | (10.0 cm x 20.7 cm x 17 cm) |
| Weight | 3.8 lb (1.7 kg) | 6.6 lb (3.0 kg) | 11.5 lb (5.2 kg) | 13.0 lb (5.9 kg) |
| | | | . 6. | |
| Shipping weight | 4 lb (1.8 kg) | 7.5 lb (3.4 kg) | 13 lb (5.9 kg) | 14.1 lb (31 kg) |



OFFICES

2211 West Casino Road Everett, Washington 98204 USA

425-353-8833

4467 White Bear Pkwy St. Paul, MN 55110 USA

800-553-6418

Testing for specifications at 25° C. Specifications subject to change without notice.