



MS-PAE SERIES | 120/240V INVERTER/CHARGER

Introduction

The MS-PAE 120/240V Series Inverter/Charger is a pure sine wave inverter designed specifically for the most demanding renewable energy applications. The MS-PAE Series is powerful, easy-to-use, and best of all, cost effective.

No series stacking required: The unique design of the MS-PAE Series can provide 120 and 240 volts output in one unit, eliminating the need to stack two units together to get 240 volts.

Parallel stacking: You can parallel up to four inverter/chargers for up to 17.6 kW of power at 120/240V. MP Panels and Router are required for parallel stacking the MS-PAE Series.

Power Factor Corrected (PFC) Charger: Our PFC charger is built into all of our inverter chargers. It uses less energy from a generator than a standard charger – 25-30% less AC current than standard chargers.



Features

- Pure sine wave – Power your TVs, computers and other sensitive electronics without worry. The pure sine wave inverter and power factor corrected charger provide clean, reliable inverter power with low total harmonic distortion (THD) of less than 5%.
- Choices – The MS-PAE Series comes in 24 and 48 volt configurations, allowing you to choose the model that is right for you.
- Versatile mounting – Mount the MS-PAE Series on a shelf or wall.
- Lightweight – The lightweight aluminum base and cover also provides noise reduction and corrosion resistance.
- Multiple ports – The MS-PAE Series provides multiple ports, including an RS485 communication port for network expansion, and a remote port.
- Accessible design – The extra large AC access cover with terminal screw block and 360° DC connection terminals with covers make this inverter more accessible when it needs to be.
- Convenient switches – The MS-PAE Series comes with an on/off inverter-mounted switch with an easy-to-read LED indicator.

Model Numbers

- MS4024PAE
- MS4448PAE

Available For

- Renewable Energy Systems
- Off-grid Power
- Back-up Power

Available Accessories

- Auto Generator Start - ME-AGS-N
- Battery Monitor Kit
- Conduit Box
- Fuse Blocks
- Remote - ME-ARC
- Remote - ME-RC
- Router - ME-ARTR
- MP and MMP Panels



Pure Sine Wave



Battery Voltage Options



Continuous Output Options



SPECIFICATIONS

	MS4024PAE	MS4448PAE
INVERTER SPECIFICATIONS		
Input battery voltage range	18 - 34 VDC	36 - 64 VDC
Nominal AC output voltage	120/240 VAC split phase ($\pm 5\%$)	120/240 VAC split phase ($\pm 5\%$)
Output frequency and accuracy	60 Hz ± 0.1 Hz	60 Hz ± 0.1 Hz
Total Harmonic Distortion (THD)	< 5%	< 5%
1 msec surge current (amps AC)	Line-Neutral: 120, Line-Line: 70	Line-Neutral: 120, Line-Line: 70
100 msec surge current (amps AC)	Line-Neutral: 72, Line-Line: 40	Line-Neutral: 75, Line-Line: 40
5 sec surge power (real watts)	5800	8500
30 sec surge power (real watts)	5200	6000
5 min surge power (real watts)	4800	5400
30 min surge power (real watts)	4500	4800
Continuous power output at 25° C	4000 VA (L-L)	4400 VA (L-L)
Maximum continuous input current	266 ADC	144 ADC
Inverter efficiency (peak)	93%	94%
Transfer time	16 msec	16 msec
Search mode (typical)	< 6 watts	< 6 watts
No load (120 VAC output, typical)	27 watts	25 watts
Waveform	Pure Sine Wave	Pure Sine Wave
CHARGER SPECIFICATIONS		
Continuous output at 25° C	105 ADC	60 ADC
Charger efficiency	85%	85%
Power factor	> .95	> .95
Input current at rated output (AC amps)	15 AAC per leg at 120/240 VAC split phase	17.5 AAC per leg at 120/240 VAC split phase
GENERAL FEATURES AND CAPABILITIES		
Transfer relay capability	2 legs at 30A per leg transfer standard on all models	
Five stage charging capability	Bulk, Absorb, Float, Equalize (requires remote), and Battery Saver™	
Battery temperature compensation	Yes, 15 ft Battery Temp Sensor standard	
Internal cooling	0 to 120 cfm variable speed drive using dual 92mm brushless DC fans	
Overcurrent protection	Yes, with two overlapping circuits	
Overtemperature protection	Yes on transformer, MOSFETS, and battery	
Corrosion protection	Yes, PCB's conformal coated, powder coated chassis/top, and stainless steel fasteners	
Listings	ETL Listed to ANSI / UL1741 and CSA STD C22.2 No.107.1-01	
Warranty	Three years parts and labor (five years when installed on MMP or MP system)	

PHYSICAL SPECIFICATIONS		
Dimensions (l x w x h)	13.75" x 12.65" x 8.0" (34.9 cm x 32.1 cm x 20.3 cm)	
Mounting	Shelf, wall (no vents on bottom), MP or MMP panels	
Weight	55 lb (24.9 kg)	55 lb (24.9 kg)
Shipping weight	62 lb (28.2 kg)	63 lb (29.6 kg)
Max operating altitude	15,000' (4570 m)	
Temperature (Operating/Non-operating)	-20° C to +60° C (-4° F to 140° F) to -40° C to +70° C (-40° F to 158° F)	
Operating humidity	0 to 95% RH non-condensing	



GENERAL NOTES

Testing for specifications at 25°C.
Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

- Safe and reliable: The MS-PAE Series is ETL Listed to the stringent requirements of UL 1741 and CSA C22.2 #107.1-01 for renewable energy installations.

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com